

SPORTSMAN®

2,200 Surge Watts

Portable Generator

1,800 Running Watts

Inverter

Dual Fuel
Gasoline or Propane Powered



EPA/CARB
approved



Includes Parallel Port!

When connected to another identical generator, the surge/running watts will double!



[NOTE]

Non-polarized Parallel Port black and white wire connections can be placed on either left or right side. (The parallel kit is sold separately)

PARALLEL KIT TERMINALS

The non-polarized parallel kit terminals are used with a parallel kit (sold separately) that will allow generators to be linked together to increase output. The black and white wire connections can be placed on either left or right side.

NOTICE:

Do not disconnect cables while the generator is running. The generator or the load may be damaged.

NOTE: Read and understand the parallel kit's instructions prior to use. Kit is for use with this unit only.

Only connect two identical Inverter Generators together using a Parallel Kit.

- Recoil Start
- 79.7cc 4 Stroke OHV Engine
- 1 Gallon Fuel Tank
- Runs 7 Hours @ 50% Load (GAS)
- Runs 18 hours @ 50% Load on 20 lbs of LPG Fuel (Propane / Gas Tank Not Included)
- 2 x 120 Volt A/C Outlets
- 1 x 12 Volt D/C Outlet
- Noise Level : < 60 dB @ 0% Load measured at 23 feet

- Engine Shut Off Switch
- Low Oil Shutdown
- Sine Wave Clean Power For Electronics
- USB Port
- 3 HP / 4,650 RPM
- Oil SAE 10W30
- Oil Capacity: 13.5 oz.
- Parallel Port Output Capability (parallel port cable sold separately)

* SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GAS

Item No.	UPC No.	Case Wt. Lbs.	Cubic Ft.	Case Qty.
GEN2200DFI	0 27077 08234 0	50.0 lbs	3.43	1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				