

2200 Surge Watts

SPORTSMAN®

Portable Generator

1800 Running Watts

Gasoline Powered

Inverter Generator

Clean & Stable
Voltage!
Reliable Power
For Sensitive
Electronics

**SINE
WAVE**

**EPA
Approved**

**CARB
Approved**



- Recoil Start
- 79.7cc 4 Stroke OHV Engine
- 1 Gallon Fuel Tank
- Runs 7 Hours @ 50% Load (GAS)
- 2 x 120 Volt A/C Outlets
- 1 x 12 Volt D/C Outlet
- Noise Level : < 60 dB @ 0% Load measured at 23 feet
- Engine Shut Off Switch
- Low Oil Shutdown
- Sine Wave Clean Power For Electronics
- 3 HP / 4,650 RPM
- Oil SAE 10W30
- Oil Capacity: 13.5 oz.
- Parallel Port Output Capability (parallel port cable sold separately)

Package Type: Color Box

Item No.	UPC No.	Case Wt. Lbs.	Cubic Ft.	Case Qty.
GEN2000I	0 27077 07975 3	50.0	3.77	1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				