

SPORTSMAN®

3000 Surge Watts

Inverter Portable Generator

2,850 Running Watts

**EPA
approved****Includes Parallel Port!**

When connected to another identical generator, the surge/running watts will double!

[NOTE]

(The parallel kit is sold separately)

Includes CO Warning feature

- 3000 Surge Watts / 2850 Running Watts
- 4-Stroke OHV Engine 208cc
- Recoil Start
- 5.5 HP Gasoline Engine
- 2 - USB Ports
- 2 - 120V A/C Outlets
- 1 - 120V RV Outlet
- Engine Run Time: 8 Hours @ 50% Load
- Low Oil Shutdown
- EPA Approved
- Noise Level: 65dB @ 0% Load at 23 feet
- Oil SAE 10W30
- Oil Capacity: 20.2 ounces
- Fuel Capacity: 3.1 gallon
- Fuel Type: Unleaded Gasoline Only 87 rating or higher
- 3,800 RPM
- Sine Wave Output
- Spark Plug Type: F7RTC

- Engine Shut Off Switch
 - Low Oil Shutdown
 - Sine Wave Clean Power For Electri
 - Parallel Port Output Capability
- (Includes Parallel Port! When connected to another identical generator, the surge/running watts will double!)
- (NOTE: The parallel kit is sold separately.)
- High Altitude Use: This generator is not recommended for high altitude use above 3,000 feet.
 - If you are using a generator above sea level, the generator may not function properly because of air flow getting through the carburetor.

Package: Brown Box**2022-08**

Item No.	UPC No.	Case Wt. Lbs.	Cubic Ft.	Case Qty.
GEN3000IOF	0 27077 07806 0	77. lbs	3.81	1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				