

SPORTSMAN®

EPA
Approved

Gasoline / LP Powered Inverter Generator Set



Clean & Stable
Voltage!
Reliable Power
For Sensitive
Electronics

**SINE
WAVE**



**PARALLEL
CONNECTION
CAPABLE**

WHEN COMBINED,
PROVIDES
**50
AMPS**

Includes Parallel Port! When connected to another identical generator, the surge/running watts will increase.

Two Generators 3,500 Surge Watts / 3,000 Running Watts Plus 1-50 Amp Parallel Cable

- Recoil Start
- 3.2 Gallon Fuel Tank
- 7 HP
- 2 x 120 Volt A/C Outlets
- 1 x 12 Volt D/C Outlet
- 1 x 120V RV Outlet
- Runs 12 Hours @ 50% Load
- Noise Level : < 69 dB @ 0% Load
- Oil SAE 10W30
- Oil Capacity: 18.6 oz.



Use Parallel Cable for combined output 7,000 Surge Watts / 6,000 Running Watts

201909

Item No.	UPC No.	Case Wt. Lbs.	Cubic Ft.	Case Qty.
GEN35DFKIT50	0 27077 08445 0	169.0	10.3	1/1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				