4,000 Surge Watts

SPORTSMAN®

Portable Generator

3,500 Running Watts

Dual Fuel Gasoline or Propane Powered







- EPA Approved
 Low Oil Shutdown
- Oil Capacity: 20 ounces Fuel Capacity: 3.9 gallon
- Noise Level: 69dB @ 0% Load
- AVR Automatic Voltage Regulation

- 4000 Surge Watts / 3500 Running Watts*
- 4-Stroke OHV Engine 212cc
- Recoil Start
- 7.0 HP Gasoline Engine
- 1 12V D/C Outlet
- 4 120V A/C Outlets
- 1 120V RV Outlet
- Engine Run Time: 10 Hours @ 50% Load
- Runs 12 hours @ 50% Load on 20 lbs of LPG Fuel
- (Propane Tank Not Included)



- Fuel Type: Unleaded Gasoline Only Octane rating 87 or higher
- 3,600 RPM
- Mobility Kit: Available Separately
- * SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GAS

Packaging: Brown Box



This generator includes a built-in Carbon Monoxide Warning Alert! The generator will automatically shut-off if dangerous levels of Carbon Monoxide is detected.

AWARNING Carbon monoxide (also known as CO) can be dangerous for humans and pets. Carbon monoxide poisoning can lead to death in a very short time. It is called "the silent killer" because it is odorless, tasteless and invisible: you may be exposed without knowing it.

NOTE: The indicator will light RED and the engine will shutdown if dangerous Carbon Monoxide levels are detected. The engine will not restart for 5 minutes. If an error in the carbon monoxide system is detected, the indicator will blink YELLOW and the engine will shutdown for five minutes.





MOVE TO FRESH AIR AND GET MEDICAL HELP IF SICK, DIZZY OR WEAK. MOVE GENERATOR TO AN OPEN, OUTDOOR AREA. POINT EXHAUST AWAY. DON'T RUN GENERATOR IN ENCLOSED AREA (E.G. NOT IN HOUSE OR GARAGE).

Item No. UPC No. Case Wt. Lbs. Cubic Ft. Case Qty.

GEN4000DF-SS 0 27077 08235 7 102.0 5.34 1

950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055