

4000 Surge Watts 3500 Running Watts

Tri Fuel Generator




GAS, LP, NG

Runs on Natural Gas, LPG or
Unleaded Gasoline

- 4 x 120 Volt A/C Outlets
- 1 x 12 Volt D/C Outlet
- 1 x 120 Volt RV Outlet
- Oil SAE 10W30
- Oil Capacity: 18.5 oz.
- 120 Volt / 60 Hz
- 3.6 Gallon Fuel Tank
- Automatic Low Oil Shutdown
- Noise Level : < 69 dB @ 0% Load
- 212cc OHV, 4 Stroke Air Cooled
- Fuel Type: Unleaded Gasoline Only 87 rating or higher
- This portable generator is not for use with gasoline/ ethanol blends with over 15% ethanol. Do not use E85 fuel.
- Run Time : 10 Hours at 50% Load (GAS)
- Run Time : 12 hours @ 50% Load (LPG) on 20 lbs of LPG Fuel
- Propane fuel hose / regulator included
- High Altitude Use: This generator is not recommended for high altitude use above 3,000 feet.
- If you are using a generator at 3,000 feet above sea level, the generator may not function properly because of air flow getting through the carburetor.
- SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GASOLINE.
- SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 20% WHEN USING NATURAL GAS VS USING GASOLINE



Package: Brown Box



Includes one each
LPG adapter and
NG adapter



Item No.	UPC	Case Wt.	Cubic Ft.	Case Qty.
GEN4000TRI	0 27077 07839 8	97.0 lbs	5.34	1

950 Hoff Road	O'Fallon, MO 63366	Phone 636.532.9888	Fax 636.537.1055
---------------	--------------------	--------------------	------------------