



Portable Generator 4,000 Surge / 3,500 Running Watts

- 7.0 HP Engine, 4 Stroke OHV
- 3.6 Gallon Fuel Tank
- Engine Shut Off Switch
- Circuit Breaker & Power Outlets
- Voltmeter Included (only shows volts)
- Run time = 10 hours @ 50% load GAS
- Run time = 12 hours @ 50% load LPG
- Dual Fuel- Runs on LP or Gasoline
- Warranty: 2 YEAR Limited Emissions
- Warranty: 1 YEAR Limited
- 4 - 120V A/C Outlets
- Noise Level: 69dB @ 0% Load
- 3,600 RPM
- Recoil Start
- Decibel < 69 db @ 0% load



ATTENTION ⚠ CO WARNING ALERT!

This generator includes a built-in Carbon Monoxide Warning Alert! The generator will automatically shut-off if dangerous levels of Carbon Monoxide is detected.

⚠ WARNING Carbon monoxide (also known as CO) can be dangerous for humans and pets. Carbon monoxide poisoning can lead to death in a very short time. It is called "the silent killer" because it is odorless, tasteless and invisible; you may be exposed without knowing it.

NOTE: The indicator will light RED and the engine will shutdown if dangerous Carbon Monoxide levels are detected. The engine will not restart for 5 minutes. If an error in the carbon monoxide system is detected, the indicator will blink YELLOW and the engine will shutdown for five minutes.



AUTOMATIC SHUTOFF - YOU MUST:



MOVE TO FRESH AIR AND GET MEDICAL HELP IF SICK, DIZZY OR WEAK. MOVE GENERATOR TO AN OPEN, OUTDOOR AREA. POINT EXHAUST AWAY. DON'T RUN GENERATOR IN ENCLOSED AREA (E.G. NOT IN HOUSE OR GARAGE).

Package: Color Box

Item No.	UPC	Case Wt.	Cubic Ft.	Case Qty.
GEN4KDF	0 27077 08442 9	102.0	5.975	1/1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				