

8,750 Surge Watt / 7000 Running Watt

**SPORTSMAN®**

# Invertor Generator

EPA  
Approved

## Dual Fuel



- 8750 Surge Watts / 7000 Running Watts\*
- 4-Stroke OHV Engine 420cc
- Recoil Start / Electric Start
- 15.0 HP Dual Fuel Engine
- (Propane Tank Not Included)
- 4 x 120 Volt GFCI A/C Outlets
- 1 x 120/240 Volt RV Outlet
- 1 x 12 Volt DC Outlet
- 1 x USB 5V
- Engine Run Time: 10 Hours @ 50% Load Gasoline Fuel
- Engine Run Time: 6 hours @ 50% Load on 20 lbs of LPG Fuel
- Low Oil Shutdown
- EPA Approved
- Noise Level: 70dB @ 0% Load at 23 Ft.
- Oil Capacity: 33.8 ounces
- Fuel Capacity: 7 gallon
- 3,600 RPM
- USB Port
- Battery Cable Included (Used for Electric Start)
- Use Battery Power Pack Instead of Motorcycle Battery to Start
- (Battery Power Pack sold separately)
- Mobility Kit Not Available
- Fuel type - Liquid Propane Gas (also commonly referred to as LP, LPG and Propane) Or Unleaded Gasoline with octane rating 87 or higher
- This portable generator is not for use with gasoline/ ethanol blends with over 15% ethanol. Do not use E85 fuel.
- High Altitude Use: This generator is not recommended for high altitude use above 3,000 feet.
- If you are using a generator above sea level, the generator may not function properly because of air flow getting through the carburetor.
- \* SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GASOLINE.

20A GFCI outlet  
50A RV outlet



### Package: Color Box

Item No.	UPC	Case Wt.	Cubic Ft.	Case Qty.
GEN85KIDF	0 27077 08441 2	148.0 lbs	7.78	1

950 Hoff Road	O'Fallon, MO 63366	Phone 636.532.9888	Fax 636.537.1055
---------------	--------------------	--------------------	------------------