

1,500 Surge Watts 2-Cycle Generator

SPORTSMAN



- 1500 Surge Watts / 900 Running Watts
- 2 HP 2-Cycle Fuel Engine
- 2 - 120V A/C Outlet
- 1 - 12V D/C Outlet
- 2 Stroke, 3600 RPM
- Recoil Start
- Displacement: 72cc
- Phase: Single
- AC Voltage: 120V @ 60Hz
- Decibel Rating less than 65 db @ 24 Feet
- Complies with EPA emissions
- Engine Run Time: 8 Hours @ 50% Load
- Fuel Tank Capacity: 1 Gallon
- Fuel: Unleaded Gas & 2-Cycle Oil Mix (50:1)
- Mix unleaded gasoline with 2-cycle oil for outdoor power equipment with 50:1 mix. (1 gal/2.5 oz)
- Includes CO Warning Feature



ATTENTION This generator includes a built-in Carbon Monoxide Warning Alert! The generator will automatically shut-off if dangerous levels of Carbon Monoxide are detected.

CO WARNING
CARBON MONOXIDE DETECTED SENSOR FAIL

WARNING Carbon monoxide (also known as CO) can be dangerous for humans and pets. Carbon monoxide poisoning can lead to death in a very short time. It is called "the silent killer" because it is odorless, tasteless and invisible; you may be exposed without knowing it.

NOTE: The indicator will light RED and the engine will shutdown if dangerous Carbon Monoxide levels are detected. The engine will not restart for 5 minutes. If an error in the carbon monoxide system is detected, the indicator will blink YELLOW and the engine will shutdown for five minutes.

AUTOMATIC SHUTOFF - YOU MUST:

+ MOVE TO FRESH AIR AND GET MEDICAL HELP IF SICK, DIZZY OR WEAK. MOVE GENERATOR TO AN OPEN, OUTDOOR AREA. POINT EXHAUST AWAY. DON'T RUN GENERATOR IN ENCLOSED AREA (E.G. NOT IN HOUSE OR GARAGE).

READ MANUAL FOR COMPLETE CO WARNING INSTRUCTIONS!

Package: 2-Color Brown Box

2022-10

Item No.	UPC No.	Case Wt. Lbs.	Cubic Ft.	Case Qty.
GENMAX1500	0 27077 08629 4	46.5	2.5	1/1
950 Hoff Road O'Fallon, MO 63366 Phone 636.532.9888 Fax 636.537.1055				